# BYG04-21-02D

比例阀用电磁铁 Electromagnet for proportional valve

- 适用于 PV72 系列电磁比例插装阀
- 螺纹连接,线圈可实现免停机更换
- 线圈内孔 φ21.5,全塑封工艺
- Applicable to PV72 series proportional cartridge solenoid valve
- Threaded connection, coil can be replaced without stopping

29.80

46 70

 $\bullet\,$  Coil inner hole  $\varphi$  21.5, full plastic sealing process

外形及连接尺寸

### **Outline and connection dimensions**





F-S characteristic curve



### DC12V 1.5A DC24V 0.75A

其它规格可定做 Other can be customized



### <u>技术</u>参数 /technical parameter

1211 2 327 recentinear parameter			
环境温度 Ambient temperature	°C	-25~50	
额定电压 Rated voltage	VDC	12	24
额定电流 Rated current	А	1.5	0.75
最大电流 Maximum current	А	1.6	0.8
额定电阻 Rated resistance	Ω	4.5	18
额定行程 Rated stroke	mm	2.5	
全行程 Full stroke	mm	3.2	
额定推力 Rated thrust	N	50	
力滞环 Force hysteresis	%	≤ 4	
电流滞环 Current hysteresis	%	≤ 4	
重复精度 Repetition accuracy	%	≤1	
工作油压 Working oil pressure	MPa	≤ 21	
防护等级 Degree of protection		IP67	
通电持续率 Power on duration	%	100	
绝缘等级 Insulation class		H (180)	
电气连接方式 Electrical connection mode		DT04-2P	

## 注意事项

### matters needing attention

- 首次使用或长期停机后启用,请先将系统内 空气排净!
- 2. 可任意方向安装,建议水平安装。
- 1. After the first use or long-term shutdown, please exhaust the air in the system first!
- 2. It can be installed in any direction, and it is recommended to install horizontally.