# BYG08-33-01MD

比例阀用电磁铁 Electromagnet for proportional valve

- 适用于电液比例螺纹插装阀
- 配备手动调整装置
- 线圈内孔 φ13,全塑封工艺
- Suitable for electro-hydraulic proportional threaded cartridge valves
- Equipped with manual adjustment device
  Coil inner hole \$\phi13\$, full plastic sealing process
- 外形及连接尺寸

#### **Outline and connection dimensions**







## 力 - 位移特性曲线

F-S characteristic curve



### DC12V 1.2A DC24V 0.6A

其它规格可定做 Other can be customized



#### 技术参数 /technical parameter

jor 2 or / ceeninear parameter			
环境温度 Ambient temperature	°C	-25~50	
额定电压 Rated voltage	VDC	12	24
额定电流 Rated current	A	1.2	0.6
最大电流 Maximum current	A	1.36	0.68
额定电阻 Rated resistance	Ω	8.5	34
额定行程 Rated stroke	mm	1.5	
全行程 Full stroke	mm	2.5	
额定推力 Rated thrust	N	22	
力滞环 Force hysteresis	%	≤ 4	
电流滞环 Current hysteresis	%	≤ 4	
重复精度 Repetition accuracy	%	≤1	
工作油压 Working oil pressure	МРа	≤ 21	
防护等级 Degree of protection		IP67	
通电持续率 Power on duration	%	100	
绝缘等级 Insulation class		H (180)	
电气连接方式 Electrical connection mode		DT04-2P	

### 注意事项

### matters needing attention

- 首次使用或长期停机后启用,请先将系统内 空气排净!
- 2. 可任意方向安装,建议水平安装。
- 1. After the first use or long-term shutdown, please exhaust the air in the system first!
- 2. It can be installed in any direction, and it is recommended to install horizontally.

BYG